

Bombas Sun Pumps

BOMBA SUMERGIBLE SIN ESCOBILLAS			2 HP		MODELO SCS 20 - 200	
PSI	CDT METROS	LPM	VOLTAJE CD MOTOR	CORRIENTE MOTOR	WATTS MOTOR	EFICIENCIA
0	0.0	106.0	120	5.90	708	0%
10	7.0	98.4	120	5.87	704	16%
20	14.1	88.9	120	5.72	686	30%
30	21.1	77.6	120	5.72	686	39%
40	28.2	64.3	120	5.53	664	45%
50	35.2	49.2	120	5.17	620	46%
60	42.3	27.6	120	4.65	558	34%
70	49.3	0.0	120	3.76	451	0%

Controlador PCB8-180

BOMBA SUMERGIBLE SIN ESCOBILLAS			2 HP		MODELO SCS 20 - 200	
PSI	CDT METROS	LPM	VOLTAJE CD MOTOR	CORRIENTE MOTOR	WATTS MOTOR	EFICIENCIA
0	0.0	117.0	135	6.84	923	0%
10	7.0	109.8	135	6.84	923	14%
20	14.1	102.2	135	6.84	923	25%
30	21.1	92.7	135	6.76	913	35%
40	28.2	83.3	135	6.63	895	43%
50	35.2	71.9	135	6.43	868	48%
60	42.3	56.8	135	6.11	825	47%
70	49.3	37.8	135	5.63	760	40%
80	56.3	10.0	135	4.69	633	14%
90	63.4	0.0	135	4.36	589	0%

Controlador PCB8-180

BOMBA SUMERGIBLE SIN ESCOBILLAS			2 HP		MODELO SCS 20 - 200	
PSI	CDT METROS	LPM	VOLTAJE CD MOTOR	CORRIENTE MOTOR	WATTS MOTOR	EFICIENCIA
0	0.0	126.8	150	7.80	1170	0%
10	7.0	120.4	150	7.80	1170	12%
20	14.1	113.6	150	7.80	1170	22%
30	21.1	106.0	150	7.77	1168	31%
40	28.2	96.5	150	7.66	1149	39%
50	35.2	87.4	150	7.52	1128	44%
60	42.3	75.7	150	7.33	1100	47%
70	49.3	62.5	150	7.03	1055	48%
80	56.3	45.4	150	6.55	983	43%
90	63.4	26.5	150	6.08	912	30%
100	70.4	0.0	150	4.99	749	0%

Controlador PCB8-180

BOMBA SUMERGIBLE SIN ESCOBILLAS			2 HP	MODELO SCS 20 - 200		
PSI	CDT METROS	LPM	VOLTAJE CD MOTOR	CORRIENTE MOTOR	WATTS MOTOR	EFICIENCIA
0	0.0	147.6	180	9.70	1746	0%
10	7.0	141.9	180	9.72	1750	9%
20	14.1	135.5	180	9.74	1753	18%
30	21.1	128.7	180	9.73	1751	25%
40	28.2	121.1	180	9.69	1744	32%
50	35.2	113.6	180	9.60	1728	38%
60	42.3	106.0	180	9.49	1708	43%
70	49.3	96.5	180	9.34	1681	46%
80	56.3	87.1	180	9.15	1647	49%
90	63.4	76.8	180	8.88	1598	50%
100	70.4	64.3	180	8.55	1539	48%
110	77.5	51.9	180	8.09	1456	45%
120	84.5	37.9	180	7.20	1296	40%
130	91.6	22.7	180	6.92	1246	27%
140	98.6	7.6	180	6.80	1224	10%
150	105.6	0.0	180	6.22	1120	0%

Bombas Sumergibles SUN PUMPS

Modelo SCS 20-200

